

# YBC 344 – QSL9G5

## COMPLETE DIESEL GENERATOR SET

ISSUE 2015

### CONTENT

DESCRIPTION	1
FEATURES	1
GENSET SPECIFICATIONS	1
ENGINE SPECIFICATIONS	2
ALTERNATOR SPECS	2
CONTROL SYSTEM	2
GENSET OPTIONS	2

### POWER RATING

#### RATING - 60HZ, 1800 RPM

PRIME RATING		STANDBY RATING	
KW	KVA	KW	KVA
275	344	300	375

## DATA SHEET SPECIFICATION 344KVA - 375KVA - 60 HZ



### Description

Younes Bros generators are fully designed to maintain optimum performance and reliability using the finest solutions for technical simplicity and robust construction

Our generators are available with **CE** certification along with the installation Quality Assurance ( **IQA** ) from Cummins and designed in facilities certified to ISO 9001

**YBC 344 - QSL9G5**

### Features

- Cummins heavy duty engines
- Stamford Class H Alternators
- Deep Sea control system
- Water cooling system
- Optional weather 7 sound protective enclosures
- Genset accepts load as per NFPA110

### Genset Specifications

Generating set KVA Prime 344 KVA Standby 375KVA, equipped with Cummins diesel engine type QSL9G5 driving at 1800 RPM.

A single bearing Stamford alternator brushless, self excited, self regulated, insulation and temperature class H, PH 0.8, 220/380V, 3 phase, 4 wire regulated at +/- 1%, 60 Hz.

## COMPLETE DIESEL GENERATOR SET

ISSUE 2015

### Engine Specifications

- BRAND : CUMMINS
- TYPE : QSL9G5
- Output prime rating : 344 KVA
- Displacement : 8.8Liter
- No of cylinders : Inline 6
- Ambient Temperature : 55°C
- Bore : 114mm
- Stroke : 145 mm
- Cycle : 4 Stroke
- Aspiration : Turbo & Charge Air Cooled
- Running speed : 1800 RPM
- Fuel Consumption : 25% - 20 liter/hour  
50% - 36 liter/hour  
100% - 63 liter/hour
- Type of governor : Electronic ( ISO 8528 Part I Class G3)
- Type of injection : Bosch HPCR



### Alternator Specifications

- Brand : Stamford
- Rated Voltage : 380 V
- Phase : 3
- Rotational Speed : 1800 RPM
- Power Factor : 0.8
- Frequency : 60 Hz

### Control System

Deep Sea Automatic Start Control module that offers an advanced range of engine monitoring and protection features

### Generator Set Options

- Engine:** Water jacket heater 220V
- Enclosure:** Sound attenuated canopy
- Alternator:** Alternator Heater  
PMG kit
- Power Panel:** 4 Poles Main Circuit Breaker

- Warranty:** 5 Years for standby application  
2 Years for prime application
- Silencer :** 9 dB attenuation industrial silencer  
25 dB residential - delivered loose

### Younes Bros s.a.r.l

- Address:** Nahr El Mott - Main Road - Beirut - Lebanon
- Contact us :** 00961-1-887886-901488-902488
- Fax :** 00961-1-901588
- Email :** info@younesbros.com

